



MODEL: DCI-BPF-FB-6P



| Description | |
|----------------------------------|--------------------------|
| Type: | Bandpass Filter |
| No. of Poles: | 6 |
| Connector Type: | N |
| Mechanical Specifications | |
| Dimensions: | W2.75" x D4.75" x H2.25" |
| Connector Spacing: | 1.25" |
| Extrusion: | Milled |
| Weight: | 1.4 lbs. |
| Mounting: | 6-32 Threaded Chassis |
| Electrical Specifications | |
| Center Frequency: | 2441.5 MHz |
| Band Width: | 83 MHz |
| SWR: | <1.3:1 |
| Return Loss: | >18 dB |
| Approximate 3 dB BW: | -/+ 43 MHz |
| Approximate 30 dB BW: | -/+ 70 MHz |
| Approximate 50 dB BW: | - 98/+ 95 MHz |
| Power Handling: | 200 Watts RMS |
| Impedance: | 50Ω |
| Temp. Drift: | Approximately 40KHz/1°C |

